

Professional 430 or 530W ATX12V 2.3 80 Plus Computer Power Supply

ATX2PW430PRO

ATX2PW530PRO



*actual product may vary from photos

DE: Bedienungsanleitung - de.startech.com

FR: Guide de l'utilisateur - fr.startech.com

ES: Guía del usuario - es.startech.com

IT: Guida per l'uso - it.startech.com

NL: Gebruiksaanwijzing - nl.startech.com

PT: Guia do usuário - pt.startech.com

For the most up-to-date information, please visit: www.startech.com

FCC Compliance Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Use of Trademarks, Registered Trademarks, and other Protected Names and Symbols

This manual may make reference to trademarks, registered trademarks, and other protected names and/or symbols of third-party companies not related in any way to StarTech.com. Where they occur these references are for illustrative purposes only and do not represent an endorsement of a product or service by StarTech.com, or an endorsement of the product(s) to which this manual applies by the third-party company in question. Regardless of any direct acknowledgement elsewhere in the body of this document, StarTech.com hereby acknowledges that all trademarks, registered trademarks, service marks, and other protected names and/or symbols contained in this manual and related documents are the property of their respective holders.

Table of Contents

Introduction	1
Packaging Contents	1
System Requirements.....	1
Installation	2
Hardware Installation	2
Specifications	4
Technical Support	6
Warranty Information	6

Introduction

The StarTech.com ATX12V 2.3/ EPS12V 2.91 series power supplies are 80 Plus® certified, providing stable power while balancing energy-efficiency. Compliant with ATX12V 2.3 standards and certified SLI® ready, this power supply offers the versatility and support for AMD or Intel CPU based entry level servers, gaming PCs and high end work stations, or a higher level energy-efficient replacement/upgrade power supply for Desktop PC's.

Packaging Contents

- 1 x ATX Power Supply
- Instruction Manual

System Requirements

- ATX compliant motherboard•
- ATX compliant computer case that fits a full sized power supply

Installation

WARNING! Computer parts can be severely damaged by static electricity. Be sure that you are properly grounded before opening your computer case. StarTech.com recommends that you wear an anti-static strap when installing any computer component. If an anti-static strap is unavailable, discharge yourself of any static electricity build-up by touching a large grounded metal surface (such as the computer case) for several seconds.

Installation of a power supply requires some mechanical skill and requires that you open your computer case to disconnect and reconnect wires. If you are unfamiliar with this kind of work, consider bringing your computer and new StarTech.com power supply to your local computer store for help.

Hardware Installation

1. Turn your computer off and any peripherals connected to the computer (i.e. printers, external hard drives, etc.).
2. If the power supply has a power switch on it, set it to the "0" position. Unplug the power cable from the rear of the power supply on the back of the computer and disconnect all other peripheral cables.
3. Remove the cover from the computer case. Refer to documentation for your computer system for details.
4. Disconnect all of the power connectors from the motherboard and peripheral devices (i.e. hard drives, CD/DVD drives, etc). Make sure to take note of each connector and where they were plugged in. Ensure there are no devices connected to the existing power supply.
5. Remove the existing power supply from the computer case. This is typically done by removing four (4) mounting screws on the outside face of the power supply. Refer to documentation for your computer system/case for specifics.
6. Install and mount the new power supply by reversing the steps used to remove the old power supply.
7. Connect the power connectors from the power supply to the motherboard and peripheral devices that were disconnected previously. Note that this power supply uses a 20+4 pin ATX connector, so it can be used on motherboards with either a 20-pin or 24-pin connector. Simply detach the extra 4-pin attachment for use on 20-pin motherboards.
8. NOTE: the detached 4-pin connector cannot be used in place of the 4-pin ATX12V (P4) connector.
9. Make sure any loose or unused cables from the power supply are away from fans and other moving parts.
10. Place the cover back onto the computer case.

11. Make sure the power switch on the power supply is set to "0", then insert the power cable into the socket on the power supply. If the old power cable looks worn or damaged in any way, replace with the supplied power cable, otherwise it is safe to reuse it.
12. Reconnect all other connectors/cables that were removed in Step. Set the power switch on the power supply to "1".

Specifications

	ATX2PW430PRO	ATX2PW530PRO
Standards	ATX12V v2.3 EPS12V v2.92	
Maximum Power Output	430W	530W
Efficiency Rating	84.08%@20% load 84.81%@50% load 82.47%@100% load	84.72%@20% load 85.61%@50% load 82.01@100% load
Fans	1 x 80mm	
Input Power	100 ~ 240VAC, 10 ~ 5A, 47 ~ 63Hz	
Operating Temperature	0°C ~ 40°C (32°F ~ 104°F) @ 90% Load	
Storage Temperature	-20°C ~ 80°C (-4°F ~ 176°F)	
Humidity	5 ~ 90% RH	
MTBF	100,000 Hours	
Dimensions (LxWxH)	140.0mm x 150.0mm x 86.0mm	
Weight	1710g	

ATX2PW430PRO Power Output

DC Output	+3.3V	+5V	+12V1	+12V2	+12V3	+12V4	-12V	+5Vsb
	24A	24A	20A	20A	20A	20A	0.5A	2.5A
Max Power	140W	396W		411.5W			6W	12.5W


ATX2PW530PRO Power Output

DC Output	+3.3V	+5V	+12V1	+12V2	+12V3	+12V4	-12V	+5Vsb
	24A	24A	20A	20A	20A	20A	0.5A	2.5A
Max Power	140W		492W				6W	12.5W
	511.5W							

Connectors




1 x ATX 20+4 pin



1 x 4+4 pin ATX12V
(8-pin EPS12V)




2 x 6-pin PCI Express



5 x 15-pin SATA



3 x 4-pin Molex Power (LP4)



1 x 4-pin Mini-Power (SP4)

Technical Support

StarTech.com's lifetime technical support is an integral part of our commitment to provide industry-leading solutions. If you ever need help with your product, visit www.startech.com/support and access our comprehensive selection of online tools, documentation, and downloads.

For the latest drivers/software, please visit www.startech.com/downloads

Warranty Information

This product is backed by a three year warranty.

In addition, StarTech.com warrants its products against defects in materials and workmanship for the periods noted, following the initial date of purchase. During this period, the products may be returned for repair, or replacement with equivalent products at our discretion. The warranty covers parts and labor costs only. StarTech.com does not warrant its products from defects or damages arising from misuse, abuse, alteration, or normal wear and tear.

Limitation of Liability

In no event shall the liability of StarTech.com Ltd. and StarTech.com USA LLP (or their officers, directors, employees or agents) for any damages (whether direct or indirect, special, punitive, incidental, consequential, or otherwise), loss of profits, loss of business, or any pecuniary loss, arising out of or related to the use of the product exceed the actual price paid for the product. Some states do not allow the exclusion or limitation of incidental or consequential damages. If such laws apply, the limitations or exclusions contained in this statement may not apply to you.

Hard-to-find made easy. At StarTech.com, that isn't a slogan. It's a promise.

StarTech.com is your one-stop source for every connectivity part you need. From the latest technology to legacy products — and all the parts that bridge the old and new — we can help you find the parts that connect your solutions.

We make it easy to locate the parts, and we quickly deliver them wherever they need to go. Just talk to one of our tech advisors or visit our website. You'll be connected to the products you need in no time.

Visit www.startech.com for complete information on all StarTech.com products and to access exclusive resources and time-saving tools.

StarTech.com is an ISO 9001 Registered manufacturer of connectivity and technology parts. StarTech.com was founded in 1985 and has operations in the United States, Canada, the United Kingdom and Taiwan servicing a worldwide market.